

ASOS ERRATA SHEET 1 (for Electronics Technicians)

Engineering Division

W/OSO321:BGM

Replacement Page for ASOS Modification Note 12

GENERAL

This errata sheet provides instructions to correct A-5 of ASOS Modification Note 12. The reason for the change is to correct parameters located on page A-5, item D, DISABLE "AT" COMMANDS, lines 42 and 45. Line 42 was changed from YES to NO. Line 45 was moved and renumbered as line 43 and the NO was changed to YES. The original line 43 was renumbered as line 44. The original line 44 was renumbered as line 45.

A corrected page A-5 is provided with this errata sheet. The areas where corrections were made are highlighted.

PROCEDURE

1. Remove page A-5 of ASOS Modification Note 12 and replace with corrected page attached to this errata sheet.

EFFECT ON OTHER INSTRUCTIONS

Replaces page A-5 of EHB-11, Section 3.6, ASOS Modification Note 12, issued March 15, 1994.

J. Michael St. Clair
Chief, Engineering Division

Attachment

- | | | | |
|-----------|--------------------------|--|-----------|
| | 28. | CHANGE TO UNILATERAL CTS? | NO |
| | 29. | CHANGE TO RTS/CTS? | NO |
| | 30. | CHANGE TO DISABLED? | YES |
| | 31. | FLOW IS DISABLED, CHANGE? | NO |
| | 32. | XON/XOFF PASS THRU DISABLED CHANGE? | |
| TALK/DATA | | | |
| | 33. | CHANGE MNP OPTIONS? | NO |
| | 34. | CHANGE DTE OPTIONS | YES |
| | 35. | ASYNC DATA CHANGE TO SYNC? | NO |
| | 36. | DTE RATE IS 9600, CHANGE? | NO |
| | 37. | 8 BIT CHAR SIZE CHANGE TO 7? | NO |
| | 38. | NO PARITY CHANGE? | NO |
| | D. DISABLE "AT" COMMANDS | | |
| | 39. | "AT" COMMAND SET ENABLE, CHANGE? | YES |
| | 40. | "AT" COMMAND SET DISABLE, CHANGE? | NO |
| | 41. | IGNORES DTR CHANGE? | NO |
| | 42. | DSR FORCED HIGH CHANGE? | YES |
| | 43. | CHANGE TO DCD FROM REMOTE? | NO |
| | 44. | DCD FORCED HIGH CHANGE? | YES |
| | 45. | DCD IS REMOTE CHANGE? | NO |
| | 46. | CTS FORCED HIGH CHANGE? | YES |
| | 47. | CHANGE TO CTS FOLLOWS RTS? | NO |
| | 48. | CHANGE TO CTS EQUALS RTS? | NO |
| | 49. | CHANGE TO CTS FOLLOWS DCD? | YES |
| | 50. | CTS FOLLOWS DOD CHANGE? | |
| TALK/DATA | | | |
| | 51. | CHANGE DTE OPTIONS? | TALK/DATA |
| | E. STORE PRESENT SETUP | | |
| | 52. | LOAD OR STORE OPTION SET? | YES |
| | 53. | LOAD FACTORY OPTION SET? | NO |
| | 54. | STORE PRESENT OPTIONS? | YES |
| | 55. | ARE YOU SURE? YES | |
| | 56. | OPTIONS ARE NOW PERMANENT (displayed for 2 seconds, then)
MODIFY CONFIGURATION? | |

TALK/DATA

V.32 9600/TRAINING

NOTE: Display will read TRAINING until modems connect, then display will change to **ON LINE**.

18. On OID-2 (OID-3) change baud rate from 2400 to 9600. Press SET UP (F3). Move cursor using arrow keys to PORT. Move cursor down to PORT A SETTINGS. Press <ENTER>. Move cursor down to TRANSMIT BAUD RATE. Press <ENTER> until 9600 is selected. Press <SHIFT> <UP ARROW>. Move cursor to EXIT. Select EXIT AND SAVE CHANGES and press <ENTER>. Answer Yes to question. OID will be communicating with ACU.

(end of procedure)

W/OSO321:BGMcCormick:713-1834:4/19/94
WP51 Files: ERRATA12.H11, EHB-11 disk 11a
Spellcheck sol 4/19/94